

2014 - 2019 Corvette: Service Bulletin: #PIC6439: Diagnostic Tip for a B1517 DTC - Battery Negative Cable - (Jun 25, 2021)

#PIC6439: Diagnostic Tip for a B1517 DTC - (Jun 25, 2021)

Subject:	Diagnostic Tip for a B1517 DTC					
Brand:	Model:	Model Year:	VIN:	Engine:	Transmi	ssion:
		from to	from to			
Chevrolet	Corvette	2014 - 2019	All	All	All	All
Involved Region or Country	North America					
Condition	The reason that a vehicle has been brought into the dealership may vary widely.					
Cause	During the initial diagnosis, a technician may find a B1517 set in one of the vehicles listed above.					
Correction						

If a B1517 is found set in any module, or even multiple modules, dealership technicians are to first inspect the battery cable connections. In many cases, the small black wire that connects to the larger battery negative cable is loose or damaged. If the vehicle history is reviewed, or the customer is further questioned, it will usually be found that a battery was recently replaced in the

vehicle. This may have been done by a tech unfamiliar with the vehicle, a different shop, or even by the customer himself.

Closely inspect the small black wire seen in the photo below. It may be loose, rotated, or pulled out of the actual terminal. Any loose connection or damage to this circuit may cause a B1517, especially with a symptom 5A.

It should also be noted that this is not a manufacturing concern, but rather this issue is caused by improper service work that was previously done on the vehicle. Resecure / repair the connection as needed.

Version 1

Modified 06/25/2021 Created on.

Online URL:

<https://www.corvetteactioncenter.com/tech/knowledgebase/article/2014-2019-corvette-service-bulletin-pic6439-diagnostic-tip-for-a-b1517-dtc-battery-negative-cable-jun-25-2021-1521.html>